

PB SERIES

BRIDGE CIRCUIT VOLTAGE OUTPUT



Analog absolute positioning

The PB series transducer includes a sensing potentiometer in a bridge circuit with adjustable zero and span controls. The completely passive circuit gives a maximum output voltage at maximum span setting of approximately 18% of the input voltage. The span adjustment allows for easy interface to a bridge amplifier. With zero position adjustable to anywhere within the total range of the transducer, voltage output is positive when extending the cable from the selected zero position and is negative when retracting from zero.

SPECIFICATIONS

GENERAL

Linearity	
2", 3", 4" & 5" Ranges	±0.25% Full Scale
10", 15", 20" & 25" Ranges	±0.15% Full Scale
All other ranges	±0.10% Full Scale
Repeatability ⁽¹⁾	±0.015% Full Scale
Resolution	Essentially Infinite
Construction	Aluminum Cover & Baseplate
Sensing Device	Precision Potentiometer
Connector	MS3102A-14S-6P
Wire Rope	Ø.016 Stainless Steel
Wire Rope Tension	See Supplemental Data ⁽²⁾ , Table 7
Wire Rope Inbound Acceleration	See Supplemental Data ⁽²⁾ , Table 7
Weight	
Up to 50"	1.0 lb. (0.45 Kg)
60" & 80"	1.4 lb. (0.63 Kg)
Dimensional Information	See Supplemental Data ⁽²⁾ , Fig. 1 & 2
Options and Accessories	See Supplemental Data ⁽²⁾


ELECTRICAL

Input Impedance	1.25KΩ
Output Impedance	1.25KΩ at max span setting
	14.4KΩ @ 51% max. span setting
Excitation Voltage	30 Volts Max. AC or DC
Output Voltage	User adjustable to a maximum of 18% of Input Voltage

ENVIRONMENTAL

Thermal Coefficient of Sensing Element	±100 PPM/°C max.
Operating temperature	-40°C to +95°C
Operating humidity	95% R.H. max. non-condensing
Vibration	15 G's 0.1 ms max.
Shock	50 G's 0.1 ms max.
Ingress Protection	NEMA 1, IP-40

CONNECTION DIAGRAM



FOOTNOTES TO SPECIFICATIONS

1. Moving to the same position from the same direction.
2. Supplemental Data section locate at end of Standard Series pages.

MODEL NUMBER CONFIGURATION

PB- 0 1 2 3 4 6 7 0 9

BASIC CONFIGURATION (FOR ALL RANGES)

PB-50-S10-N0S-10C

0 RANGE
2.....2" (50 mm)
3.....3" (75 mm)
4.....4" (100 mm)
5.....5" (125 mm)
10.....10" (250 mm)
15.....15" (390 mm)
20.....20" (500 mm)
25.....25" (640 mm)
30.....30" (750 mm)
40.....40" (1000 mm)
50.....50" (1250 mm)
60.....60" (1500 mm)
80.....80" (2000 mm)

1 WIRE ROPE
S.....Ø.016 (0.4 mm) Stainless Steel
N.....Ø.018 (0.45 mm) Nylon Jacketed Stainless Steel

2 WIRE ROPE TENSION
1.....Standard (50 G Units to 50")
2.....Reduced (See Table 7 for Value)
3.....Increased (100G on Units With Ranges From 2" to 50")

3 WIRE ROPE EXIT DIRECTION
Use Number designators shown

4 DUST WIPER OPTION
N.....No dust wiper
D.....Dust Wiper Included

6 ELECTRICAL OUTPUT POLARITY
S.....Standard (increasing output as wire rope is extended)
R.....Reversed (decreasing output as wire rope is extended)

7 CONNECTOR LOCATION
Use Number designators shown

9 ELECTRICAL INTERFACE
C.....Mating Connector Included
K.....Mating Connector Omitted*
T.....Terminal Strip
*Electrical cable with mating connector may be ordered separately as part number 10028-xM where 'x' is the length required in meters.

STANDARD SERIES

SUPPLEMENTAL DATA



LIFE*

Ranges 2" to 5"	5,000,000 full stroke cycles
Ranges 10" to 25"	500,000 full stroke cycles
Ranges 30" to 80"	250,000 full stroke cycles


*With 1K ohm potentiometer, wire rope misalignment 2° maximum at full stroke, relatively dust free environment, and with nylon jacketed wire rope

OPTION DESCRIPTIONS

OPTION	OPTION DESIGNATOR	DESCRIPTION								
WIRE ROPE	N	Replaces standard stainless steel wire rope with Ø.018 nylon jacketed wire rope. Increases wire rope life dramatically but may increase non-linearity by as much as ±0.05% of full scale.								
Nylon jacketed wire rope										
WIRE ROPE TENSION	2	Reduces the overall tension in the wire rope and increases wire rope life. Dynamic response of the transducer is reduced due to the reduced inbound acceleration capability.								
Reduced Wire Rope Tension										
Increased Wire Rope Tension	3	Increases tension in the wire rope which increases the dynamic response of the transducer. On selected units with range of 50" (1250 mm) or less, inbound acceleration capability is 100G's. Wire rope life may be adversely affected by the HG option.								
DUST WIPER	D	Lubricated wiper strips dust and debris from wire rope as it retracts into case. Adds 0.36" (9 mm) height to wire rope exit location.								
POTENTIOMETER VALUE	2,3,4	Non-standard potentiometer linearity is as follows:								
Non-standard potentiometer (applies to PA series only)		<table><tr><th>RANGE</th><th>LINEARITY</th></tr><tr><td>5" and Below</td><td>±1.00% of full scale</td></tr><tr><td>10" to 25"</td><td>±0.50% of full scale</td></tr><tr><td>30" and above</td><td>±0.25% of full scale</td></tr></table>	RANGE	LINEARITY	5" and Below	±1.00% of full scale	10" to 25"	±0.50% of full scale	30" and above	±0.25% of full scale
		RANGE	LINEARITY							
		5" and Below	±1.00% of full scale							
		10" to 25"	±0.50% of full scale							
30" and above	±0.25% of full scale									
Note: This option is subject to potentiometer availability.										
ELECTRICAL OUTPUT POLARITY	R	Output is at a maximum when wire rope is fully retracted. Output decreases as wire rope is extended. Does not apply to velocity or encoder signal.								
Reversed output										
ELECTRICAL INTERFACE	T	Replaces connector with a terminal strip.								
Terminal strip										

10067 – AUXILIARY WIRE ROPE EXTENSION KIT

The auxiliary wire rope extension may be used to facilitate mounting the transducer remotely from the measurement point. The clip on the extension attaches to the eye fitting on the transducer. The eye fitting on the opposite end, which is identical to the fitting on the transducer, mounts to the moving element. The extension kit is also available with the clip end unterminated for situations where it is more convenient to size the wire rope length during installation. Clip and crimp fitting are included with the unterminated version.



10067-¹-CM-²

1 DIMENSION "L"	Specify Dimension "L" in centimeters to the nearest whole centimeter
NOTES: 1. 1 cm = 0.394", 1 inch = 2.54 cm 2. Shortest length "L" is 5 cm (approximately 2")	
2 UNTERMINATED CLIP END	Leave Blank..... Completed Kit (No designator required)
U	Unterminated Clip End (clip and crimp sleeve included in kit)

REPLACEMENT WIRE ROPE KITS

The replacement Wire Rope Kit includes a new wire rope with all end terminations, wire rope guide, felt dust wiper where applicable and installation instructions. To order, replace 'xx' in the part number with the applicable measurement range in inches.

- 10107-xx Replacement Wire Rope Kit**—Standard Ø.016" Stainless Steel Wire Rope.
- 10108-xx Replacement Wire Rope Kit**—Ø.018" Nylon Jacketed Stainless Steel Wire Rope.
- 10127-xx Replacement Wire Rope Kit**—Standard Ø.016" Stainless Steel Wire Rope with Dust Wiper.
- 10128-xx Replacement Wire Rope Kit**—Ø.018" Nylon Jacketed Stainless Steel Wire Rope with Dust Wiper.

STANDARD SERIES

SUPPLEMENTAL DATA



ADDITIONAL OPTIONS


TABLE 7

PA, PB, P420 & P510 SERIES								EP SERIES		V & VP SERIES		
Range Designator	Range		Wire Rope Standard Tension		Wire Rope Standard Acceleration	Wire Rope Reduced Tension		Wire Rope Reduced Acceleration		Wire Rope Reduced Tension		Wire Rope Reduced Acceleration
	(in)	(mm)	(oz)	(N)	(G's)	(oz)	(N)	(G's)		(oz)	(N)	(G's)
2	2	50	34	9.5	>50	16	4.4	28	—	16	4.4	14
3	3	75	24	6.7	>50	14	3.9	16	—	14	3.9	15
4	4	100	24	6.7	>50	11	3.1	12	—	11	3.1	15
5	5	125	34	9.5	>50	8	2.2	7	—	8	2.2	6
10	10	250	34	9.5	>50	16	4.4	28	16	4.4	19	14
15	15	390	24	6.7	>50	14	3.9	16	—	14	3.9	15
20	20	500	24	6.7	>50	11	3.1	12	—	11	3.1	14
25	25	640	34	9.5	>50	8	2.2	7	8	2.2	7	6
30	30	750	24	6.7	>50	14	3.9	16	—	14	3.9	15
40	40	1000	24	6.7	>50	11	3.1	12	—	11	3.1	12
50	50	1250	34	9.5	>50	8	2.2	7	8	2.2	7	5
60	60	1500	24	6.7	27	7	1.8	2	7	1.8	5	6
80	80	2000	19	5.3	16	5	1.4	2	5	1.4	2	3


DIMENSIONAL INFORMATION

STANDARD SERIES | PA, PB, P420, P510, EP & V SERIES

RANGES TO 50" (1250 mm)



RANGES TO 60" (1500 mm) and 80" (2000 mm)



We are here for you. Addresses and Contacts.

Headquarter Switzerland:

Angst+Pfister Sensors and Power AG
Thurgauerstrasse 66
CH-8050 Zurich
Phone +41 44 877 35 00
sensorsandpower@angst-pfister.com

Office Germany:

Angst+Pfister Sensors and Power Deutschland GmbH
Edisonstraße 16
D-85716 Unterschleißheim
Phone +49 89 374 288 87 00
sensorsandpower.de@angst-pfister.com

Office North America:

Angst+Pfister North America Inc.
10391 Brecksville Rd.
US-Brecksville, OH 44141
Phone +1 440 375-5212
info.apus@angst-pfister.com

Scan here and get an overview of personal contacts!



<https://sensorsandpower.angst-pfister.com/en/>
